

RN00066

PN5190 B2 firmware release v03.05

Rev. 1.5 — 9 December 2024

Release notes

Document information

Information	Content
Keywords	PN5190, PN5190 B2, NFC frontend controller
Abstract	Contains information about a specific release product and component information



1 Document purpose

This document describes the tested functionality and limitations of the firmware PN5190 B2 FW v03.05.

It also describes the release summary, release history, known issues, work-arounds, limitations, and recommendations.

The functionality and limitations of the hardware and product support material (for example, customer development board and support software) are described in separate documents.

PN5190 B2 FW v03.05 is identical in features and functionality with PN5190 B1 FW v02.0A except for the firmware update (HDLL commands) which was updated for a crypto-assisted download to achieve higher security.

PN5190 B2 uses crypto-assisted download mode commands, where the opcodes are different compared with PN5190 B1 which uses the legacy download mode commands.

The user manual UM11942 (PN5190 instruction layer) explains the different opcodes used for download mode commands in detail.

2 PN5190 B2 firmware version information

PN5190 B2 software package version (including host utilities): v03.05

PN5190 B2 secure firmware version: v03.05

Note: *This firmware version is meant only for the PN5190 B2 IC. This firmware cannot be used for the PN5190 B1 IC version.*

For new designs, it is recommended to always use the latest firmware version available.

3 Features supported in this release

This section provides the features supported in this firmware/software version release.

3.1 RF protocols

Table 1. RF protocols

Feature/functionality
Reader mode A (106/212/424/848 kbit/s)
Reader mode B (106/212/424/848 kbit/s)
Reader mode FeliCa (212/424 kbit/s)
Reader mode ISO/IEC15693 (26/53/106/212Kbps) - all data rates as specified in data sheet
Reader mode ISO/IEC18000 3M3 - all data rates as specified in data sheet
Host card emulation / Card mode ISO/IEC 14443 A-106, A-212, A-424, A-848
Peer-Peer passive communication (ISO18092, PI106, PI212, PI424, PT106, PT212, PT424)
Peer-Peer passive communication with proprietary baud rates (PI212, PI424, PI848, PT212, PT424, PT848)

3.2 Other system features/functionality protocols

Table 2. Other system features

Feature/functionality
Low-power card detection (LPCD) and ultra low-power card detection (ULPCD)
Dynamic power control
Automatic waveshape control
Automatic receiver control
Internal DC-DC for TX driver
Over temperature protection (automatic shutdown of TX drivers and entering low-power mode (Standby), over temperature event on GPIO)
Current limiter (automatic shutdown of TX drivers and event notification to host)
Supported to route analog and digital signal on AUX1(analog) and GPIO0 (digital).
Trimming of RF parameters (TX_NOV, current sensor, NFCLD, RFLD).

3.3 Compliancy with this firmware and PNEV5190B hardware (customer development board)

Table 3. Compliancy with this firmware and PNEV5190B hardware (customer development board)

Feature/Functionality
EMVCo L1 digital compliance
ISO 10373-PCD digital compliance
ISO 10373-PICC digital compliance
NFC Forum CR11 analog and digital compliance. NFC Forum CR13 internally qualified.
ISO 23917 Peer-Peer Passive compliance

4 Version history

This section contains the firmware release version history.

The previously released hardware version had been **"B1"**.

The new hardware version is **"B2"**. There is no change in hardware functionality or software functionality features compared with **"B1"**.

Only the ROM code has been updated for the **"B2"** IC version.

The below table provides the firmware version history including feature updates and issues fixed.

Table 4. Firmware updates from v03.04 to v03.05

SI No.	Function/feature update
1	<p>Added new LPCD command option which makes the IC enter LPCD mode and returns with an Autocoll Event if an external RF is detected.</p> <p>In SWITCH_MODE_LPCD(0x23) command, bControl field option LPCD_WITH_AUTOCOLL_EVENT (0x13) is added to support LPCD with Autocoll event when wake-up occurs due to load change/Ext RF from LPCD standby scenarios.</p> <p>Added EEPROM field to configure the time-out for Autocoll expiry: Name: LpcdWithAutocollExpiryInterval. Address Offset: 0xC EE Size: 1 Byte. Description: This field is the time before which Autocoll expires when LPCD is used with Autocoll option. 1unit - 100 ms. The default is 10 ms.</p>
2	<p>Added a new command CTS_FAST_CONFIGURE (0x2B) which both configures and enables CTS. For Enabling CTS, the Length should be 0x27(including both Configs and Enabling bytes). This command cannot be used for disabling CTS. First fast Init+Configure takes about 50 ms, second time onwards about 50 µs.</p>
3	<p>Added configuration to initialize the pullup/down state of SPI Pads (ATX Pins) in the secure flash init. This feature is disabled by default.</p> <p>Added the following EEPROM fields for reconfiguration of SPI pad configurations: Name: EnableHIFPadsReConfig. Address Offset: 0xC EF Size:1 Byte. Description: Enable/Disable reconfiguration of the SPI Pads configuration. Name: SPIPadReConfig. Address Offset: 0xC F0 Size: 4 Bytes. Description: SPI Pads PullUp/Down Configuration.</p>
4	<p>Fixed an issue which prevented exit from the Autocoll in some scenarios when external RF is removed.</p>
5	<p>Fixed an issue that caused changes in amplitude of response during Host Card emulation, when higher VDDPA Values are used in APC TX entries.</p>

Table 5. Firmware updates from v03.03 to v03.04

SI No.	Function/feature update
1	Feature implemented DPR (Dynamic Power Regulation). Added new register DYNAMIC_POWERLEVEL_REG (Reg Addr: 0x64).
2	Feature implemented LFO timing calibration using frequency meter for higher LPCD pulse interval accuracy. Added new EEPROM setting LFO_TRIM_CALIBRATION (EEPROM Addr.0xCED).
3	Updated the DPC algorithm for higher control accuracy.
4	Updated command GET_CRC_USER_AREA (Command code: 0x29).

Table 6. Firmware updates from v03.02 to v03.03

SI No.	Function/feature update
1	Resolved the issue of DPC not recovering to expected VDDPA regulation during load change conditions, when in some corner case scenarios the DPC has to manage other priority tasks.

Table 7. Firmware updates from v03.01 to v03.02

SI No.	Function/feature update
1	Fixed an issue where in increased leakage current in SPI_NSS (ATX_C) during low-power mode operation.

Table 8. Firmware updates from v03.00 to v03.01

SI No.	Function/feature update
1	Fixed an issue where in commands UPDATE_RF_CONFIGRUATION and GET_RF_CONFIGURATION commands when used for TX index 0x0F (ISO180003m3_TARI_18.88us) and 0x10 (ISO180003m3_TARI_9.44us).
2	Fixed an issue of not-restoring the analog TX settings when switching from reader mode to card mode. Removing of type-b detection during Autocoll. Supporting only Type-A and Type-F detection as part of Autocoll procedure.
3	Introduced a new EEPROM configuration: ENABLE_ULFO_TRIM_CALIBRATION (0xCEC). This configuration enables/disables the calibration of wake-up counter value based on the ULFO accuracy measured with frequency meter with Xtal as reference. Note: <i>This feature must be used only when Xtal is available and configured for use</i>
4	Deprecated the P2P active communication target mode functionality.

Table 9. Firmware updates in v03.00

SI No.	Function/feature update
1	All of the features and functionalities present in PN5190 B1 FW v02.06 is included in this FW version. In a nut-shell, below are incremental features are added in PN5190 B2 v03.00 and PN5190 B1 v02.06. <ul style="list-style-type: none"> Added new command:GET_CRC_USER_AREA[0x29]: This command is used to calculate the CRC for the complete User area including Protocol area. This command helps customer to ensure the integrity of their RF and analog settings by detecting manipulation of this area. Modified SOF timing: In this FW version, we have modified the protocol settings of TypeB106 such that it supports SOF timing adjustment. We also provide better results during the EMVCo L1 analog test.

5 Recommendations, known limitations, and precautions

This section provides the known limitations in the FW/HW recommendations

5.1 Known limitations

1. With the default FDT settings for ISO18000 (dwFDT_18000_DefVal parameter, which is 1.26 ms), performance @ -40 °C is reduced when TARI = 18.88 μs. This shall be appropriately adjusted for better performance.
2. Randomly, PN5190 FW does not respond to the first REQA from an iPhone 12 Mini phone with HCE Mode + LPCD enabled.

5.2 Recommendations

The following clock parameters for Xtal are recommended for active communication on the customer development board PNEV5190B and 45 mm x 45 mm antenna.

Table 10. Recommendations for v03.00 and above

Address	Parameter name	Default value	Value for active communication
1	ANA_PLL_CTRL_XTAL	0x00	0xC1
2	ANA_PLL_CTRL_XTAL	0x8A	0x13
3	ANA_PLL_CTRL_XTAL	0xEA	0xE8
4	ANA_PLL_CTRL_XTAL	0xA6	0xA6

5.3 Precautionary notes

1. Do not disable the DPC and activate the RF field for IC's connected to antennas matched "Symmetric" (for example, customer development board antenna). Possible damage to the transmitter drivers due to overcurrent over a long period might occur.
2. PN5190 B1 samples cannot be upgraded with the PN5190 B2 FW. However, PN5190 B2 samples can be updated with this FW version.
Note: *The FW upgrade/downgrade to v03.02 (3.2) must be done in a power-stable environment. This is applicable for PN5190B2EV/C130 and PN5190B2HN/C130 parts only. PN5190B2EV/C131 and PN5190B2HN/C131 contain FW v03.02 (3.2) by default.*
3. The ULPCD requires a specific power configuration with no DC-DC active and requires modifications to both the customer development board PNEV5190B EEPROM settings as described in the application notes.

6 Revision history

Table 11. Revision history

Document ID	Release date	Description
RN00066 v.1.5	9 Dezember 2024	• PN5190 B2 firmware v03.05 release: Section 4 "Version history" updated.
RN00066 v.1.4	19 June 2024	• PN5190 B2 firmware v03.04 release: Section 4 "Version history" updated.
RN00066 v.1.3	23 May 2024	• PN5190 B2 firmware v03.03 release: Section 4 "Version history" updated.
RN00066 v.1.2	07 November 2023	• PN5190 B2 firmware v03.02 release: Section 4 "Version history" updated.
RN00066 v.1.1	08 September 2023	• PN5190 B2 firmware v03.01 release: Section 4 "Version history" updated.
RN00066 v.1.0	03 May 2023	• PN5190 B2 firmware v03.00 release: Section 4 "Version history" updated.

Legal information

Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <https://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Suitability for use in non-automotive qualified products — Unless this document expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

Evaluation products — This evaluation product is intended solely for technically qualified professionals, specifically for use in research and development environments to facilitate evaluation purposes. It is not a finished product, nor is it intended to be a part of a finished product. Any software or software tools provided with an evaluation product are subject to the applicable license terms that accompany such software or software tools. This evaluation product is provided on an "as is" and "with all faults" basis for evaluation purposes only and is not to be used for product qualification or production. If you choose to use these evaluation products, you do so at your risk and hereby agree to release, defend and indemnify NXP (and all of its affiliates) for any claims or damages resulting from your use. NXP, its affiliates and their suppliers expressly disclaim all warranties, whether express, implied or statutory, including but not limited to the implied warranties of non-infringement, merchantability and fitness for a particular purpose. The entire risk as to the quality, or arising out of the use or performance, of this evaluation product remains with user.

In no event shall NXP, its affiliates or their suppliers be liable to user for any special, indirect, consequential, punitive or incidental damages (including without limitation damages for loss of business, business interruption, loss of use, loss of data or information, and the like) arising out of the use of or inability to use the evaluation product, whether or not based on tort (including negligence), strict liability, breach of contract, breach of warranty or any other theory, even if advised of the possibility of such damages.

Notwithstanding any damages that user might incur for any reason whatsoever (including without limitation, all damages referenced above and all direct or general damages), the entire liability of NXP, its affiliates and their suppliers and user's exclusive remedy for all of the foregoing shall be limited to actual damages incurred by user based on reasonable reliance up to the greater of the amount actually paid by user for the evaluation product or five dollars (US\$5.00). The foregoing limitations, exclusions and disclaimers shall apply to the maximum extent permitted by applicable law, even if any remedy fails of its essential purpose and shall not apply in case of willful misconduct.

HTML publications — An HTML version, if available, of this document is provided as a courtesy. Definitive information is contained in the applicable document in PDF format. If there is a discrepancy between the HTML document and the PDF document, the PDF document has priority.

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately. Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at PSIRT@nxp.com) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

NXP B.V. — NXP B.V. is not an operating company and it does not distribute or sell products.

Licenses

Purchase of NXP ICs with NFC technology — Purchase of an NXP Semiconductors IC that complies with one of the Near Field Communication (NFC) standards ISO/IEC 18092 and ISO/IEC 21481 does not convey an implied license under any patent right infringed by implementation of any of those standards. Purchase of NXP Semiconductors IC does not include a license to any NXP patent (or other IP right) covering combinations of those products with other products, whether hardware or software.

Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners.

NXP — wordmark and logo are trademarks of NXP B.V.

DESFire — is a trademark of NXP B.V.

EdgeVerse — is a trademark of NXP B.V.

FeliCa — is a trademark of Sony Corporation.

I2C-bus — logo is a trademark of NXP B.V.

MIFARE — is a trademark of NXP B.V.

MIFARE Classic — is a trademark of NXP B.V.

MIFARE Plus — is a trademark of NXP B.V.

NTAG — is a trademark of NXP B.V.

Tables

Tab. 1.	RF protocols	4	Tab. 6.	Firmware updates from v03.02 to v03.03	6
Tab. 2.	Other system features	4	Tab. 7.	Firmware updates from v03.01 to v03.02	6
Tab. 3.	Compliance with this firmware and PNEV5190B hardware (customer development board)	4	Tab. 8.	Firmware updates from v03.00 to v03.01	6
Tab. 4.	Firmware updates from v03.04 to v03.05	5	Tab. 9.	Firmware updates in v03.00	6
Tab. 5.	Firmware updates from v03.03 to v03.04	6	Tab. 10.	Recommendations for v03.00 and above	7
			Tab. 11.	Revision history	8

Contents

1	Document purpose	2
2	PN5190 B2 firmware version information	3
3	Features supported in this release	4
3.1	RF protocols	4
3.2	Other system features/functionality protocols	4
3.3	Compliance with this firmware and PNEV5190B hardware (customer development board)	4
4	Version history	5
5	Recommendations, known limitations, and precautions	7
5.1	Known limitations	7
5.2	Recommendations	7
5.3	Precautionary notes	7
6	Revision history	8
	Legal information	9

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.
