

UG10387

i.MX Linux Yocto Build Accelerator

Rev. 2.0 — 27 August 2026

User guide

Document information

Information	Content
Keywords	UG10387, i.MX, Linux, LF6.18.2_1.0.0, sstate-cache, Yocto Build Acceleration
Abstract	The i.MX Linux Yocto Build Accelerator is a solution that reduces the time to build Yocto-based images for i.MX MPU platforms.



1 Introduction

The i.MX Linux Yocto Build Accelerator is a solution that reduces the time to build Yocto-based images for i.MX MPU platforms.

By using the caching and mirroring mechanisms of Yocto, the build duration can be reduced from approximately 4 hours to 10 minutes. The build duration depends on the chosen machine configuration and the presence of the prebuilt artifacts.

2 Description

The Build Accelerator consists of two archives that can be used independently or together:

- [LF_6.18.2-1.0.0_YOCTO-DOWNLOADS.tar](#) contains:
 - The Yocto layers repositories.
 - The source tarballs downloaded during the BitBake `fetch` process. It contains all sources required to build the `imx-image-full`, `imx-image-multimedia`, `imx-image-core`, or `core-image-minimal` image and the corresponding SDK. This enables the Yocto to build the above images offline, with no additional downloads required.
- [LF_6.18.2-1.0.0_YOCTO-SSTATE-CACHE.tar](#) contains:
 - The Yocto layers repositories.
 - The Yocto shared-state cache of prebuilt packages. This cache enables Yocto to build `core-image-minimal`, `imx-image-core`, and the corresponding SDK without any compilation, and to accelerate the build of other images/SDKs.
 - The Hash Equivalence database: enables BitBake to use the shared-state cache.

Note: Due to the large size of the archives, use the download manager.

3 Fully accelerated configurations

The following configurations are fully accelerated, but other configurations can benefit as well.

- MACHINE

Table 1. Fully accelerated MACHINE

i.MX 8	i.MX 9
• <code>imx8qmmek</code> • <code>imx8qxp0mek</code> • <code>imx8mq-evk</code> • <code>imx8mm-lpddr4-evk</code> • <code>imx8mm-ddr4-evk</code> • <code>imx8mn-lpddr4-evk</code> • <code>imx8mn-ddr4-evk</code> • <code>imx8mp-lpddr4-evk</code> • <code>imx8mp-ddr4-evk</code> • <code>imx8ulp-lpddr4-evk</code> • <code>imx8ulp-9x9-lpddr4x-evk</code>	• <code>imx91-11x11-lpddr4-evk</code> • <code>imx91-9x9-lpddr4-qsb</code> • <code>imx91-11x11-lpddr4-frdm</code> • <code>imx93-11x11-lpddr4x-evk</code> • <code>imx93-14x14-lpddr4x-evk</code> • <code>imx93-9x9-lpddr4-qsb</code> • <code>imx93-11x11-lpddr4x-frdm</code> • <code>imx943-19x19-lpddr5-evk</code> • <code>imx943-19x19-lpddr4-evk</code> • <code>imx95-15x15-lpddr4x-evk</code> • <code>imx95-15x15-lpddr4x-frdm</code> • <code>imx95-19x19-lpddr5-evk</code>

- DISTRO
 - fsl-imx-xwayland
- IMAGE
 - core-image-minimal
 - imx-image-core

4 Usage

1. Create your development directory. For example:

```
mkdir imx-yocto-accelerator
cd imx-yocto-accelerator
```

2. Install Yocto + package sources and/or precompiled cache. Install at least one of the package sources or precompiled cache.

- a. To use the LF_6.18.2-1.0.0_yocto-downloads.tar (package sources):

```
tar xvf LF_6.18.2-1.0.0_yocto-downloads.tar
```

- b. To use the LF_6.18.2-1.0.0_yocto-sstate-cache.tar (prebuilt binaries):

```
tar xvf LF_6.18.2-1.0.0_yocto-sstate-cache.tar
```

3. Set up your MACHINE, DISTRO, and build directory. For example:

```
cd imx-yocto-bsp
DISTRO=fsl-imx-wayland MACHINE=imx8mp-lpddr4-evk source imx-setup-release.sh
-b build
```

4. Add the following configurations into your conf/local.conf file:

```
DL_DIR = "${BSPDIR}/downloads"
SSTATE_DIR = "${BSPDIR}/sstate-cache"
PERSISTENT_DIR = "${BSPDIR}/persistent"
```

Explanation of key variables:

DL_DIR: Sets the central storage location for downloaded sources.

SSTATE_DIR: Directory for the sstate cache used to accelerate builds.

PERSISTENT_DIR: Contains the Hash Equivalence database.

5. Build your preferred image. For example:

```
bitbake imx-image-core
```

6. If needed, build the SDK for your preferred image. For example:

```
bitbake -c populate_sdk imx-image-core
```

5 Acronyms

[Table 2](#) lists the acronyms used in this document.

Table 2. Acronyms

Acronym	Description
BSP	Board Support Package
MPU	Microprocessor Unit

6 References

[Table 3](#) lists the references used to supplement this document.

Table 3. Related documentation/resources

Document	Link/how to access
<i>i.MX Yocto Project User's Guide</i> (document UG10164)	UG10164

7 Note about the source code in the document

Example code shown in this document has the following copyright and BSD-3-Clause license:

Copyright 2026 NXP Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials must be provided with the distribution.
3. Neither the name of the copyright holder nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT HOLDER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

8 Revision history

[Table 4](#) summarizes the revisions to this document.

Table 4. Revision history

Document ID	Release date	Description
UG10387 v.2.0	27 August 2026	Applicable to the Linux BSP release LF6.18.2_1.0.0.
UG10387 v.1.0	12 May 2026	Initial public release, applicable to the Linux BSP release LF6.12.49_2.2.0.

Legal information

Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <https://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Suitability for use in non-automotive qualified products — Unless this document expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

HTML publications — An HTML version, if available, of this document is provided as a courtesy. Definitive information is contained in the applicable document in PDF format. If there is a discrepancy between the HTML document and the PDF document, the PDF document has priority.

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately. Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at PSIRT@nxp.com) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

NXP B.V. — NXP B.V. is not an operating company and it does not distribute or sell products.

Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners.

NXP — wordmark and logo are trademarks of NXP B.V.

Contents

1 Introduction 2

2 Description 2

3 Fully accelerated configurations 2

4 Usage 3

5 Acronyms 3

6 References 5

7 Note about the source code in the document 5

8 Revision history 5

Legal information 6

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.