# og Products Fact Sheet

# **MC33291** Eight Output Switch with SPI Interface (0.6 $\Omega$ R<sub>DS(ON)</sub>)

## DESCRIPTION

The 33291 is a versatile low-side smart switch incorporating an 8-bit serial shift register to control the 8-bit parallel output latch to provide control of the eight independent output power (ON/OFF) switches. This device is very useful to drive solenoids, relays, lamps, DC-motors, and other moderate current load (0.5 A) applications.

The 33291 interfaces directly with microcontrollers to control various inductive or incandescent loads. The circuit's innovative monitoring and protection features include very low standby current, SPI cascadable fault reporting, internal 53 V clamp on each output, output specific diagnostics, and independent shutdown of outputs.

## 33291 SIMPLIFIED APPLICATION DIAGRAM



#### **APPLICATIONS**

- Aircraft Systems
- Automotive Systems
- Robotics
- · Farm Equipment
- Industrial Actuator Controls
- Small DC-Motor Controls
- Marine Systems
- Incandescent Lamp Control
- Applications where low-side switch control with diagnostics is necessary

PERFORMANCE	TYPICAL VALUES
Outputs	8
R <sub>DS(ON)</sub> @ 25°C	0.6 Ω
Operating Voltage	5.5 – 26.5 V
Peak Current	1.0 A each output
Control	SPI
Operating Temperature	$-40^{\circ}C \leq T_A \leq 125^{\circ}C$
Junction Operating Temperature	$-40^{\circ}C \le T_J \le 150^{\circ}C$



# Power Actuation

Low-Side Switches



#### **FEATURES**

- Designed to Operate Over Wide Supply Voltages of 5.5 V to 26.5 V
- Interfaces to Microprocessor Using 8-Bit SPI I/O Protocol up to 3.0 MHz
- + 1.0 A Peak Current Outputs with Maximum  $R_{DS(ON)}$  of 1.6  $\Omega$  at  $T_J$  150°C
- Outputs Current-Limited to Accommodate In-Rush Currents Associated with Switching Incandescent Loads
- Output Voltages Clamped to 53 V During Inductive Switching
- Maximum Sleep Current (I<sub>PWR</sub>) of 25 μA
- Maximum of 4.0 mA I<sub>DD</sub> During Operation
- Devices available for comparison are in the Analog Product Selector Guide - SG1002 and Automotive Product Selector Guide - SG187

PROTECTION	DETECT	LIMITING	SHUT DOWN	AUTO RETRY	STATUS REPORTING
Overvoltage	٠		•		•
Overcurrent/SC	•	•	•	•	•
Overtemperature	٠		٠	•	
Open Load	٠				٠

### QUESTIONS

- Do you need to reduce system complexity for switching multiple loads using a microcontroller?
- Do you have very little PC board space available for load control?
- Do you require multiple high-efficiency switches to control capacitive, incandescent, or inductive loads over a wide temperature range?
- Are you looking for an easy-to-design-in solid state switch, capable of switching eight different loads?
- Do you need a "smart" switch with programmable internal protection features as well as fault reporting?
- Do you need multiple switches that can be controlled from a microcontroller via SPI protocol?

## **CUSTOMER BENEFITS**

**RCHIVE INFORMATION** 

- Low system cost, minimal component count, simplified circuitry, and minimal board space
- Simplified system design with direct interfacing to microprocessor
- Simplified inductive load driving due to internally clamped outputs
- Capable of switching capacitive, incandescent, or inductive loads
- Versatile outputs capable of parallel operation accommodating increased output load current combinations or for the reduction of R<sub>DS(ON)</sub>
- Capable of PWM-ing load

# ORDERING INFORMATION

Device	Temperature Range (T <sub>A</sub> )	Package
**33291DW	-40°C to 125°C	24 SOICW
**33291DWR2		
Data Sheet Orde	r Number	MC33291

\*\*Prefix Index:

PC = Engineering Samples; MC = Production

Contact Sales for Evaluation Kit Availability



24 SOICW 1.27 mm Pitch 15.4 mm x 7.5 mm Body

Freescale <sup>™</sup> and the Freescale logo are trademarks of Freescale Semiconductor, Inc. All other product or service names are the property of their respective owners. © Freescale Semiconductor, Inc. 2006. All rights reserved.

