

56F8014

Socket Board for Flash Programming
User Guide

56F8000
16-bit Digital Signal Controllers

56F8014SBUG
Rev. 0
04/2005

freescale.com



Document Revision History

Version History	Description of Change
Rev. 0	Initial Release

TABLE OF CONTENTS

Preface 1-v

**Chapter 1
Introduction**

1.1 56F8014 Socket Board Architecture 1-1

**Chapter 2
Technical Summary**

2.1 32-Pin LQFP Socket 2-1

2.2 32-Pin PDIP Socket. 2-2

2.3 JTAG Connector 2-2

2.4 Daughter Card Connector 2-2

2.5 Power-On LED 2-2

2.6 Manual Reset. 2-2

2.7 Test Points. 2-2

**Appendix A
56F8014 Socket Board Schematics**

**Appendix B
56F8014 Socket Board Bill of Material**



LIST OF FIGURES

1-1 Connecting the 56F8014 Socket Board & 56F8014 Demonstration Board 1-1

1-2 Connecting the 56F8014 Socket Board 1-2



Preface

This reference manual describes the hardware on the 56F8014 Socket Board in detail.

Audience

This document is intended for application developers or a production team who wish to program an application into the Flash memory on a Freescale 56F8014 part before it is mounted on a printed circuit board.

Organization

This manual is organized into two chapters and two appendixes.

- **Chapter 1, Introduction**, provides an overview of the 56F8014 Socket Board and its features.
- **Chapter 2, Technical Summary**, describes the 56F8014 Socket Board's hardware in detail.
- **Appendix A, 56F8014 Socket Board Schematics**, contains the schematics of the 56F8014 Socket Board.
- **Appendix B, 56F8014 Socket Board Bill of Material**, provides a list of the materials used on the 56F8014 Socket Board.

Suggested Reading

More documentation on the 56F8014 part may be found at URL:

www.freescale.com

Notation Conventions

This manual uses the following notational conventions:

Term or Value	Symbol	Examples	Exceptions
Active High Signals (Logic One)	No special symbol attached to the signal name	A0 CLKO	
Active Low Signals (Logic Zero)	Noted with an overbar in text and in most figures	$\overline{WE}$ OE	In schematic drawings, Active Low Signals may be noted by a backslash: /WE
Hexadecimal Values	Begin with a "\$" symbol	\$0FF0 \$80	
Decimal Values	No special symbol attached to the number	10 34	
Binary Values	Begin with the letter "b" attached to the number	b1010 b0011	
Numbers	Considered positive unless specifically noted as a negative value	5 -10	Voltage is often shown as positive: +3.3V
Blue Text	Linkable on-line	...refer to Chapter 7, License	
Bold	Reference sources, paths, emphasis	...see: http://www.freescale.com/	

Definitions, Acronyms, and Abbreviations

Definitions, acronyms and abbreviations for terms used in this document are defined below for reference.

EOnCE™	Enhanced On-Chip Emulation; a debug bus and port was created to enable a designer to create a low-cost hardware interface for a professional-quality debug environment
JTAG	Joint Test Action Group; a bus protocol/interface used for test and debug
LED	Light Emitting Diode
56F8014	A Freescale controller with motor control peripherals
OnCE™	On-Chip Emulation, a debug bus and port created to allow a means for low-cost hardware to provide a professional-quality debug environment
PCB	Printed Circuit Board
ZIF	Zero Insertion Force

References

The following sources were referenced to produce this manual:

- [1] *DSP56800E Reference Manual*, DSP56800ERM, Freescale Semiconductor, Inc.
- [2] *56F8000 Peripheral Reference Manual*, MC56F8000RM, Freescale Semiconductor, Inc.
- [3] *56F8014 Technical Data*, MC56F8014, Freescale Semiconductor, Inc.



Chapter 1

Introduction

The 56F8014 Socket Board provides a means to program the Flash memory in a 56F8014 controller, then allows the 56F8014 controller to be removed and placed onto another printed circuit board.

Some packages are not available at publication.

1.1 56F8014 Socket Board Architecture

The 56F8014 Socket Board contains a Zero Insertion Force LQFP-32 socket and a Zero Insertion Force PDIP-32 socket, as shown in [Figure 1-1](#). This combination of sockets allows both 56F8014 package types to be easily supported. Additionally, the PCB includes a JTAG connector, manual reset pushbutton switch and Daughter Card connector.

The 56F8014 Socket Board is designed to be used with a 56F8014 Demonstration Board. The power supply and JTAG interface POD used with the 56F8014 Demonstration Board are needed to provide an operational Flash programming platform.




Figure 1-1. Connecting the 56F8014 Socket Board & 56F8014 Demonstration Board

An interconnection diagram is shown in [Figure 1-2](#), connecting the PC, the external +9.0V DC power supply, the 56F8014 Socket Board and the 56F8014 Demonstration Board.




Figure 1-2. Connecting the 56F8014 Socket Board

Perform the following steps to connect the 56F8014 Socket Board:

1. Connect the 56F8014 Demonstration Board to the 56F8014 Socket Board by pressing the two boards together, using P2 on the 56F8014 Demonstration Board and P1 on the 56F8014 Socket Board.
2. Connect the parallel extension cable to the Parallel port of the host computer.
3. Connect the other end of the parallel extension cable to the JTAG interface POD.
 - Connect the ribbon cable from the JTAG interface POD to J1 on the 56F8014 Socket Board, shown in [Figure 1-2](#). This provides the connection which allows the host computer to download code to the 56F8014 part on the 56F8014 Socket Board.
4. Make sure that the external +9.0V DC, 450mA power supply is **not** plugged into a +120V AC power source.
5. Connect the 2.1mm output power plug from the external power supply into P1 on the 56F8014 Demonstration Board, shown in [Figure 1-2](#).
6. Apply power to the external power supply. The green Power-On LED on the 56F8014 Demonstration Board, LED7, and LED1 on the 56F8014 Socket Board will illuminate when power is correctly applied.

Chapter 2

Technical Summary

Some packages are not available at publication.

The 56F8014 Socket Board is designed to be combined with the 56F8014 Demonstration Board. This combination provides a Flash programming platform for the 56F8014 part. The main features of the 56F8014 Socket Board, with board and schematic reference designators, include:

- 32-Pin LQFP ZIF Socket, an open-top press-down, spring-loaded Zero Insertion Force socket by CTI/WELLS [U1]
- 32-Pin PDIP ZIF Socket, a lever-controlled Zero Insertion Force Socket by Aries [U2]
- JTAG interface connector [J1]
- Daughter Card connector, which allows the connection of the 56F8014 Demonstration Board [P1]
- LED power indicator [LED1]
- Manual Reset Pushbutton [S1]

2.1 32-Pin LQFP Socket

The 56F8014 Socket Board uses a CTI/WELLS 32-pin LQFP Zero Insertion Force (ZIF) socket, 7007-032-1-07, designated as U1 on the board. Pin 1 of the package should be aligned with pin 1 of the socket, which is positioned where the U1 reference designator is located. The socket is spring loaded, allowing the user to press down on the outer ring of the socket, forcing the contact pins to pull away from the package well area. The user then places the part requiring Flash memory programming into the socket's package well area. When the user releases the outer ring of the socket, the contact pins extend to press against the package pins, making an electrical contact with the part.

NOTE: Parts should only be installed or removed from the LQFP-32 socket when power is **not** present on the 56F8014 Socket Board. Also, only one socket should have a part present at one time.

2.2 32-Pin PDIP Socket

The 56F8014 Socket Board uses an ARIES 32-pin PDIP Universal Zero Insertion Force (ZIF) socket, 32-6554-11, designated as U2 on the board. The locking action of the socket is controlled by a lever arm on the side of the socket. When the lever arm is raised, the socket's contact pins are released, allowing the removal or insertion of the part. When the lever arm is lowered, the socket's contact pins press against the pins on the part, providing an electrical connection.

NOTE: Parts should only be installed or removed from the PDIP-32 socket when power is **not** present on the 56F8014 Socket Board. Also, only one socket should have a part present at one time.

2.3 JTAG Connector

The 56F8014 Socket Board provides a JTAG Connector, J1. This connector allows the PC to communicate with a 56F8014 part in the LQFP-32 socket or in the PDIP-32 socket.

2.4 Daughter Card Connector

The 56F8014 Socket Board uses a Daughter Card Connector, P1. This connector provides power to the 56F8014 Socket Board via the 56F8014 Demonstration Board. Power (+3.3V DC) is present on pin 1 of P1 and the ground is present on pin 3 of P1.

2.5 Power-On LED

The 56F8014 Socket Board provides a Power-On LED, LED1, which illuminates when power is applied to the 56F8014 Socket Board.

2.6 Manual Reset

The 56F8014 Socket Board provides a Manual Reset Pushbutton, S1, which allows the manual generation of a reset signal to the 56F8014 part in either the U1 or U2 socket.

2.7 Test Points

The 56F8014 Socket Board provides two power monitoring test points, TP1 and TP2. TP1 is connected to +3.3V and TP2 is connected to digital ground.

Appendix A

56F8014 Socket Board Schematics




Figure A-1. 32-Pin Sockets




Figure A-2. Daughter Card Connector

Appendix B

56F8014 Socket Board Bill of Material

Qty	Description	Ref. Designators	Vendor Part #
Sockets			
1	32-Pin LQFP Socket	U1	CTI/WELLS, 7007-032-1-07
1	32-Pin PDIP Socket	U2	ARIES, 32-6554-11
Resistors			
1	270 Ω , 5%, 0805	R1	SMEC, RC73L2A271JT
2	10K Ω , 5%, 0805	R2, R3	SMEC, RC73L2A103JT
1	47K Ω , 5%, 0805	R4	SMEC, RC73L2A473JT
Switches			
1	Pushbutton Switch	S1	Panasonic, EVQ-PAD07K
LEDs			
1	Green LED, 1206	LED1	Agilent, HSMG-C650
Capacitors			
1	47 μ F, 16V DC,ELECT-C	C1	Panasonic, ECE-V1CA470WR
Connectors			
1	40x2 Header	P1	SAMTEC, TSW-140-07-S-D
1	7x2 JTAG Header	J1	SAMTEC, TSW-107-07-S-D
Test Points			
1	+3.3V Test Point	TP1	KEYSTONE, 5000, RED
1	GND Test Point	TP2	KEYSTONE, 5001, BLACK
Miscellaneous			
4	Rubber Feet		3M SJ5018BLKC

INDEX

Numerics

56F8014 [vii](#)

E

Enhanced On-Chip Emulation

EOnCE [vii](#)

EOnce [vii](#)

J

Joint Test Action Group

JTAG [vii](#)

JTAG [vii](#)

L

LED [vii](#)

Light Emitting Diode

LED [vii](#)

O

OnCE [vii](#)

On-Chip Emulation

OnCE [vii](#)

P

PCB [vii](#)

Printed Circuit Board

PCB [vii](#)

Z

Zero Insertion Force

ZIF [vii](#)

ZIF [vii](#)

How to Reach Us:

Home Page:

www.freescale.com

E-mail:

support@freescale.com

USA/Europe or Locations Not Listed:

Freescale Semiconductor
Technical Information Center, CH370
1300 N. Alma School Road
Chandler, Arizona 85224
+1-800-521-6274 or +1-480-768-2130
support@freescale.com

Europe, Middle East, and Africa:

Freescale Halbleiter Deutschland GmbH
Technical Information Center
Schatzbogen 7
81829 Muenchen, Germany
+44 1296 380 456 (English)
+46 8 52200080 (English)
+49 89 92103 559 (German)
+33 1 69 35 48 48 (French)
support@freescale.com

Japan:

Freescale Semiconductor Japan Ltd.
Headquarters
ARCO Tower 15F
1-8-1, Shimo-Meguro, Meguro-ku,
Tokyo 153-0064, Japan
0120 191014 or +81 3 5437 9125
support.japan@freescale.com

Asia/Pacific:

Freescale Semiconductor Hong Kong Ltd.
Technical Information Center
2 Dai King Street
Tai Po Industrial Estate
Tai Po, N.T., Hong Kong
+800 2666 8080
support.asia@freescale.com

For Literature Requests Only:

Freescale Semiconductor Literature Distribution Center
P.O. Box 5405
Denver, Colorado 80217
1-800-441-2447 or 303-675-2140
Fax: 303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.



Freescale™ and the Freescale logo are trademarks of Freescale Semiconductor, Inc. All other product or service names are the property of their respective owners. This product incorporates SuperFlash® technology licensed from SST.

© Freescale Semiconductor, Inc. 2005. All rights reserved.