



# Multisensory Enablement Kit Based on i.MX 8QuadMax Applications Processors

The i.MX 8QuadMax Multisensory Enablement Kit (MEK) is ideal for safety-certifiable and efficient performance requirements.

The NXP i.MX 8QuadMax multisensory enablement kit (MEK) provides a comprehensive platform for quick evaluation and development of the Arm® Cortex® A72 + A53 Cortex-M4F based i.MX 8QuadMax and i.MX 8QuadPlus applications processors as well as the NXP PF8100 power management integrated circuit (PMIC) solution and sensors.

The MEK offers a high-level integration to support graphics, video, image processing, audio, and voice functions. Complete with highly optimized drivers and software, the i.MX 8QuadMax and i.MX 8QuadPlus processors enable broad-based applications for the embedded industrial and automotive markets.

The kit includes an LVDS-to-HDMI adapter for simple out-of-the-box bring up. It has LPDDR4, eMMC, and QSPI memory options, a 10/100/1000 Ethernet port, USB 3.0 connectors and PCIe® high-speed interfaces ideal for connected, high-performance embedded applications. For audio, video, and HMI evaluations, it brings out LVDS and MIPI-DSI connectors, and a headphone 3.5 mm audio jack.

The i.MX 8QuadMax MEK consists of a CPU board and an optional baseboard MCIMX8-8X-BB (ordered separately). The LVDS-to-HDMI adapter board is included with the MCIMX8QM-CPU. Extended audio features are supported by an audio card (IMX-AUD-IO) which is included with the baseboard.

## TARGET APPLICATIONS

- ▶ Automotive—instrument cluster, infotainment, display audio, rear seat entertainment, smart antenna, vehicle-to-vehicle (V2X), gateway and camera systems
- ▶ Industrial vehicle—avionics cockpit display, in-flight entertainment, train and heavy equipment human-machine interface (HMI)
- ▶ Advanced industrial HMI and control—PLC, I/O controller, home/building control
- ▶ Robotics—drone, mobile service robot
- ▶ Building control—fire and security panel, elevator control, HVAC control
- ▶ Healthcare—patient monitor
- ▶ Networking—specialty gateway, low-end video conference terminal
- ▶ Mobile payment—payment systems
- ▶ General-purpose HMI solutions
- ▶ Advanced vision for assistance, tracking and object detection
- ▶ Machine learning with high compute based systems
- ▶ Artificial intelligence analytics and scalable learning



## GRAPHICS, VIDEO, AND AUDIO

The MEK has hardware accelerated video, graphics, and audio processing capabilities. The integrated video supports encode and decode for h.264 as well as decode for h.265. The graphics engine and display processor support rich 3D and 2D user interfaces while the Tensilica® HiFi 4 DSP supports audio pre- and post- processing, key word detection and speech recognition for hands-off interaction. Applications like infotainment, clusters, display audio, HMI, surveillance, and robotics can take advantage of the high level of multimedia integration.

## HMI AND CONNECTIVITY

Today, HMI must respond accurately, and in milliseconds, to touch screen and gesture inputs. Connectivity is a must, demanding increasingly faster and more reliable wired and wireless capabilities associated with security to protect sensitive data and privacy. The i.MX 8QuadMax MEK provides capabilities for development of these key functionalities.

## i.MX 8QuadMax MEK FEATURES

CPU Board Part Number: MCIMX8QM-CPU	
Processor	<ul style="list-style-type: none"> <li>NXP® i.MX 8QuadMax</li> <li>2 x Arm® Cortex®-A72 @ up to 1.6 GHz</li> <li>4 x Arm Cortex-A53 @ up to 1.2 GHz</li> <li>1 GB L2 cache</li> <li>2 x Arm Cortex-M4 @ 266 MHz</li> </ul>
Power Management	<ul style="list-style-type: none"> <li>NXP MMPF8100 PMIC</li> </ul>
Memory	<ul style="list-style-type: none"> <li>3 GB LPDDR4 memory, x32</li> <li>32 GB eMMC 5.0</li> <li>64 MB Octal SPI Flash</li> </ul>
Display/Camera Connectors	<ul style="list-style-type: none"> <li>2 x MIPI-DSI / LVDS connectors</li> <li>Camera MIPI-CSI</li> </ul>
Audio	<ul style="list-style-type: none"> <li>Audio codec</li> <li>Microphone and headphone jacks</li> </ul>
Connectivity	<ul style="list-style-type: none"> <li>1 x full-size SD/MMC card slot</li> <li>1 GB Ethernet with AVB (x2)</li> <li>1 x USB 3.0 Type C</li> </ul>
Debug	<ul style="list-style-type: none"> <li>JTAG connector</li> <li>Serial to USB connector</li> </ul>
Additional Feature	<ul style="list-style-type: none"> <li>1x PCIe® 3.0</li> <li>1 x USB 3.0 with PHY</li> <li>3 x CAN/CAN FD</li> <li>1 x media local bus (MLB150)</li> <li>2 x 4-channel ADC converters</li> <li>2 x Enhanced Serial Audio Interface</li> </ul>
OS Support	<ul style="list-style-type: none"> <li>Linux®</li> <li>Android™</li> <li>FreeRTOS</li> </ul>
Expansion Connector	<ul style="list-style-type: none"> <li>M.2 connector (PCIe, USB, UART, I²C and I²S)</li> </ul>

## i.MX 8QUADMAX MEK



## i.MX 8QUADMAX MEK CONTENTS

### CPU board (standalone)

- ▶ i.MX 8QuadMax MEK CPU board
- ▶ Power supply
- ▶ Quick Start Guide
- ▶ USB 3.0 Type C to Type A
- ▶ USB 2.0 Type A to Type Micro
- ▶ LVDS to HDMI adapter card

### Baseboard (ordered separately)

- ▶ i.MX 8/8X Baseboard
- ▶ i.MX 8/8X audio board

## SOFTWARE AND TOOLS

Hardware design files, software tools and board support packages (BSPs) for Linux®, Android™ and FreeRTOS are available from NXP to use as a reference for starting designs. QNX, Green Hills®, other commercial operating systems, and tools are also available from NXP's ecosystem partners. Additional information can be found at [www.nxp.com/MCIMX8QM-CPU](http://www.nxp.com/MCIMX8QM-CPU).

i.MX 8QuadMax MEK Baseboard Features		
Part Number	Connectivity	Expansion Connector
MCIMX8-8X-BB	<ul style="list-style-type: none"> <li>1 x I²C auxiliary connector</li> <li>1 x tamper head</li> <li>1 x parallel CSI connector</li> <li>1 x UART, 2 x CAN</li> <li>1 x µUSB OTG connector</li> <li>1 x audio-in connector,</li> <li>1 x audio-out connector</li> <li>1 x 10/100/1000 Ethernet connector</li> <li>Muxed w/ Audio port)</li> </ul>	<ul style="list-style-type: none"> <li>Arduino® Connector/MikroBus Interface</li> </ul>

There are a number of accessory boards that pair with the i.MX 8QM MEK CPU board and baseboard including support for cameras and displays. Visit [www.nxp.com/i.MX8-ACCESSORY-BOARDS](http://www.nxp.com/i.MX8-ACCESSORY-BOARDS) to see the complete list.

[www.nxp.com/iMX8](http://www.nxp.com/iMX8) and [imxcommunity.org](http://imxcommunity.org)

NXP and the NXP logo are trademarks of NXP B.V. All other product or service names are the property of their respective owners. Arm and Cortex and Keil are registered trademarks of Arm Limited (or its subsidiaries) in the EU and/or elsewhere. All rights reserved. © 2019 NXP B.V.

Document Number: i.MX8QuadMaxMEKFS REV 0