


LFBGA81; Reel dry pack, SMD, 13" Q1/T1 standard product orientation Orderable part number ending ,518 or Y Ordering code (12NC) ending 518

Rev. 1 — 22 February 2016

Packing information

1. Packing method





LFBGA81; Reel dry pack, SMD, 13" Q1/T1 standard product orientation Orderable part number ending ,518 or Y Ordering code (12NC) ending 518

Table 1. Dimensions and quantities

	SPQ/PQ (pcs)		Outer box dimensions I × w × h (mm)
330 × 16	1000	1	$342\times 338\times 49$

[1] d = reel diameter; w = tape width.

Packing quantity dependent on specific product type.
 View ordering and availability details at NXP order portal, or contact your local NXP representative.

2. Product orientation

Q1/T1 Q2/T3 Q3/T4 Q4/T2 saa-014313	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
Tape pocket quadrants	Ball 1 is in quadrant Q1/T1
Fig 2. Product orientation in carrier tape	

3. Carrier tape dimensions




Table 2.Carrier tape dimensionsIn accordance with IEC 60286-3.

A ₀ (mm)	B ₀ (mm)	K ₀ (mm)	T (mm)	P ₁ (mm)	W (mm)
9.40 ± 0.10	9.40 ± 0.10	$\textbf{1.80} \pm \textbf{0.10}$	0.3 ± 0.05	12.0 ± 0.10	16 ± 0.30

LFBGA81; Reel dry pack, SMD, 13" Q1/T1 standard product orientation Orderable part number ending ,518 or Y Ordering code (12NC) ending 518

4. Reel dimensions




Table 3.Reel dimensionsIn accordance with IEC 60286-3.

A [nom]	W2 [max]	B [min]		D [min]
(mm)	(mm)	(mm)		(mm)
330	22.4	1.5	12.8	20.2

LFBGA81; Reel dry pack, SMD, 13" Q1/T1 standard product orientation Orderable part number ending ,518 or Y Ordering code (12NC) ending 518

5. Barcode label




Table 4. Barcode label dimensions

	Reel barcode label I × w (mm)	
100 × 75	100 × 75	

LFBGA81; Reel dry pack, SMD, 13" Q1/T1 standard product orientation Orderable part number ending ,518 or Y Ordering code (12NC) ending 518

6. Revision history

Table 5.Revision history

Document ID	Release date	Packing document status	Change notice	Supersedes
SOT643-1_518	20160222	Packing information	-	-

Limited warranty and liability

Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

© NXP Semiconductors N.V. 2016.

All rights reserved.

For more information, please visit: http://www.nxp.com For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 22 February 2016 Document identifier: SOT643-1_518